



High-Capacity Wide-Range DC Power Supply

PXT Series

Maximum 20 kW output in a 3U size Supports a maximum voltage of 1500 V Select input voltage from 200 Vac (3-phase) or 400 Vac (3-phase) Bleeder ON/OFF function Output ON/OFF delay function One-control parallel operation function (up to 10 units of the same model) Touch panel for intuitive operation LAN, USB, RS232C, external analog control (isolated type) standard

ES France - Département Puissance Energie 127 rue de Buzenval BP 26 - 92380 Garches

 \bigcirc



Tél. 01 47 95 99 45 Fax. 01 47 01 16 22

2 🖂 e-Si

e-mail : tem@es-france.com Site Web : www.es-france.com

NEW

Excellent size and versatility. This high-capacity DC power supply is an optimal solution.

C E CA

The PXT Series of high-performance, high-capacity, wide-range DC power supplies offers a maximum rated output of 20 kW in a compact 3U size. In addition to variable internal resistance, bleeder ON/OFF, and output ON/OFF delay functions, the PXT series has various communication interfaces (LAN, USB, and RS232C as standard). It can be used as a standalone device or integrated into testing equipment. Furthermore, the excellent heat dissipation design guarantees an ambient operating temperature of 50°C, making the unit suitable for harsh, high-temperature testing environments. The PXT Series is also highly scalable, and its capacity can be increased to 200 kW in parallel operation (up to 10 units).



High-Capacity Wide-Range DC Power Supply

PXT Series

Features

- Maximum 20 kW output in a 3U size
- Supports a maximum voltage of 1500 V
- Select input voltage from 200 Vac (3-phase) or 400 Vac (3-phase)
- Bleeder ON/OFF function
- Output ON/OFF delay function
- Full-load continuous operation is possible even at ambient temperatures as high as 50 °C (122 °F)
- One-control parallel operation function (up to 10 units of the same model)
- Touch panel for intuitive operation
- LAN, USB, RS232C, external analog control (isolated type) standard
- External control I/O is standard for both NPN and PNP type PLCs

Lineup / Main Specifications

| Specifications | Output | | Ripple noise | Power flu | uctuation | Load va | ariation | Input current | Weight | |
|----------------|-----------|-----|--------------|-----------|-----------|---------|----------|---------------|--|-----------|
| Madal | CV | cc | Rated power | cv | CV | cc | CV | сс | AC 200 V (3-phase 3-wire) / 400 V (3-phase 3-wire) | Approx. |
| woder | V | Α | kW | mVrms | mV | mA | mV | mA | A | kg(lbs) |
| PXT20K-500 | 0 to 500 | 120 | 20 | 100 | ±100 | ±240 | ±250 | ±240 | 80/40 | 38(83.78) |
| PXT20K-1500 | 0 to 1500 | 30 | 20 | 300 | ±300 | ±60 | ±750 | ±60 | 80/40 | 37(81.57) |

• Output Power Range

 \bigcirc

2.25 to 3 times mains-powered operation

The PXT series has an operating range of 2.25 to 3x power ratio, which allows for a wide range of voltage and current setting combinations. For example, the PXT20K-500 can seamlessly operate from 500 V-40 A to 166.6 V-120 A within the rated output power range of 20 kW.





ES France - Département Puissance Energie 127 rue de Buzenval BP 26 - 92380 Garches



Tél. 01 47 95 99 45 Fax. 01 47 01 16 22



0 V



NEW

• Space and Cost-Saving

Comparison of PAT500-80TM (40 kW) and PXT20K-500 x 2 units (40 kW)



• Low Ripple Noise

This switching-type power supply has low ripple noise. *PXT20K-500: Specified value 700 mVp-p (100 mVrms)



• Excellent Transient Response Characteristics

A transient response of 6 ms or less* ensures high-quality output waveforms even when the current changes abruptly.

*The time required for the output voltage to return within \pm (0.1 % + 10 mV) of the rated output voltage when the CV mode response is set to FAST. The output current fluctuation value is 50 % to 100 % of the maximum current at the set output voltage.



• Optimized for Different Purposes and Applications, with Selectable Response Speeds

Required response speed of power supply equipment varies depending on test conditions and load specifications. The PXT series can change the response speed of the power supply as desired to suit the application.

| Hode LAN | | 604 B | .088A -8. 8W | 01V | <u>-</u> | |
|-------------|-----------------|-------|-----------------------------|---------|----------|--|
| Respon | se / Slev | v Rat | e | | | |
| Respons | e | Slev | v Rate | | | |
| CV | FAST | C\ | / [V/ms] | 25 | \$ | |
| cc | FAST | c | [A/ms] | 3 | 0 | |
| | | | | | | |
| Home Ou | itp.it tting | | | | | |
| Model | Operation | Mode | | Slew ra | ate | |
| DYT20K-500 | CV [V/n | ns] | 0.125 / 1. | 25 / 12 | .5 / 25 | |
| FX120N-300 | CC [A/n | ns] | 0.03/0.3 | 3/3/6 | | |
| DYT20K 1500 | CV [V/ms] | | 0.375 / 3.75 / 37.5 / 75 | | | |
| FA1201-1500 | CC [A/ms] | | 0.0075 / 0.075 / 0.75 / 1.5 | | | |

East No Load Fall Time

• Excellent Versatility Thanks to Wide-Range Output

PXT20K-500 × 2 units 600 V 500 V 400 V 300 V single-range models example 200 V PAT160-250TM PAT500-80TM 100 V PAT250-160TM οv PAT350-114TM 100 A 200 A 240 A 0 A

Covers multiple single-range models!

WIDE RANGE DC Power Supply

Bleeder ON/OFF Function

Turning the bleeder function on quickly discharges the electrical charge accumulated in the load when the OUTPUT was turned off and allows the output voltage to be lowered. A battery connected to the output terminal will be discharged when the bleeder function is on, even if the OUTPUT is turned off. In such cases, unnecessary discharge can be prevented by turning the bleeder function off.

| ltem | Description |
|---------|---|
| Enable | Turns the bleeder function on. Sink current flows when the output is off. |
| Disable | Disables the bleeder function. Prevents unintended discharge when output is turned off. However, a low sink current will still flow due to the resistance inside the PXT series. The reference values of the internal resistance are as follows: PXT20K-500: approx. 55 k Ω PXT20K-1500: approx. 560 k Ω |

Priority Operation Mode

Mode of operation can be set, as constant voltage (CV), constant current (CC), or constant power (CP), when output is turned on. Overshoot can be prevented by setting CC mode priority when batteries, power supplies, etc. are connected.

• Equipped with Touch Panel Display

 \boxtimes

By pressing or swiping a finger on the display, on-screen items can be selected, or numerical values set.

The display is pressure-sensitive and can be operated even with gloves.



e-mail : tem@es-france.com

Site Web : www.es-france.com





Tél. 01 47 95 99 45

Fax. 01 47 01 16 22

• External Control Function

The EXT CONT connector on the rear panel can be used to control the PXT series with external devices. The general-purpose digital input and output terminals can be assigned any function, facilitating system construction in combination with other measurement devices. Digital I/O standard for both NPN and PNP type PLCs. Analog I/O is isolated from output terminals as standard, allowing safe analog control from PLC.

| connector pin | number | Re | ar panel | |
|-----------------------|------------------|---------|------------|---|
| 13 000000000 25 | 1 00000 14 | C Q. | | |
| Terminal No. | Method | I/O | Name | Description |
| 1 | Digital | 0 | OUT Ch.1 | General-purpose output terminal |
| 2 | Digital | 0 | OUT Ch.2 | General-purpose output terminal |
| 3 | Digital | 0 | OUT Ch.3 | General-purpose output terminal |
| 4 | - | - | DO COM | Digital output common |
| 5 | - | - | DI COM | Digital input common |
| 6 | Digital | 1 | IN Ch.1 | General-purpose input terminal |
| 7 | Digital | I | IN Ch.2 | General-purpose input terminal |
| 8 | Digital | Ι | IN Ch.3 | General-purpose input terminal |
| 9 | - | 0 | +12 V OUT | 12 V reference voltage available for digital input |
| 10 | - | - | - | Not used |
| 11 | - | - | A COM | Analog signal common |
| 12 | Analog | 0 | VMON | Voltage monitor |
| 13 | Analog | 0 | IMON | Current monitor |
| 14 | Digital | 0 | OUT Ch.4 | General-purpose output terminal |
| 15 | Digital | 0 | OUT Ch.5 | General-purpose output terminal |
| 16 | Digital | 0 | OUT Ch.6 | General-purpose output terminal |
| 17 | - | - | DO COM | Digital output common |
| 18 | - | - | DI COM | Digital input common |
| 19 | Digital | 1 | IN Ch.4 | General-purpose input terminal |
| 20 | Digital | I | IN Ch.5 | General-purpose input terminal |
| 21 | Digital | 1 | H ALARM IN | HIGH alarm EXT HIGH occurrence |
| 22 | - | - | 12 V COM | 12 V reference voltage common |
| 23 | - | - | A COM | Analog signal common |
| 24 | Analog | I | EXT CV | Voltage control in the constant voltage mode |
| 25 | Analog | I | EXT CC/CP | Current control in the constant current / power modes |

| Method | Function |
|---|--|
| Analog input | Setting of voltage and current values |
| Analog output | Monitoring of voltage and current values |
| General-purpose isolated digital input (Ch.1 to ch.5) *Photocoupler isolated input (Supports both current sink and source) | Output ON/OFF from DC OUTPUT terminal LOW alarm generation / deactivation Start / Stop totalizer measurement Reset totalized value Measurement trigger input Preset memory recall |
| Digital input (Ch.6) | HIGH alarm generation (Fixed) |
| General-purpose isolated digital output (Ch.1 to ch.6) *Semiconductor relay output | Monitor output status of DC OUTPUT terminal Power-on monitor Alarm monitoring Operating mode monitoring Preset memory monitoring |

General-purpose isolated digital input terminals are available from Ch.1 to Ch.5. Any setting value from the items listed on the right can be selected.



General-purpose isolated digital output terminals are available from Ch.1 to Ch.6. Any setting value from the items listed on the right can be selected.

| Node LAN | | 500 | 0.000 A 0 | A -0.05V | _ | ►OFF | ►EXT DIN BUSY |
|----------|----------|------|--------------|----------|----------|---|--|
| EXTO | Config | | | 3 | 13 | ► OUTPUT ON ► POWER ON | MEM1 ACT TIME MEM2 ACT TIME |
| DIGIC | OUT Char | nnel | | | | ►H ALARM OUT | ►RELAY DRIVE |
| Ch.1 | OFF | 0 | Ch.4 | OFF | 0 | ►L ALARM OUT | |
| Ch.2 | OFF | 0 | Ch.5 | OFF | 0 | ►CC STATUS►CV STATUS | |
| | | | | | | | |

Sequence Function

Preset operations can be run continuously. Total of 30 programs, and up to 10,000 steps can be created for all programs. Programs stored in the unit's memory, and data can be exported to a USB memory stick from the front panel.



Variable Internal Resistance Function

Function can change the output voltage value in constant voltage operation, according to the output current value based on the set resistance value. Simple simulation of Internal resistance of rechargeable batteries and wire harnesses etc.



| Item | PXT20K-500 | PXT20K-1500 |
|--------------------|-------------------------------|-----------------|
| Setting range | 0 Ω to 5250 m Ω | 0 Ω to 63000 mΩ |
| Setting resolution | 1 mΩ | 5 mΩ |

• I-V Characteristic Function

By registering multiple arbitrary points on the I-V characteristics, arbitrary I-V characteristics can be set for each CC and CV operation mode. Arbitrary points can be registered from 3 to 100, making it possible to simulate the I-V characteristics of rechargeable batteries and other devices.



 \bowtie

 Score
 Voltage [V]
 Current [A]

 1
 0
 20.000

| 2 | 300 | 20.000 | |
|---|-----|--------|---|
| 3 | 360 | 18.000 | |
| 4 | 400 | 16.000 | |
| 5 | 500 | 10.000 | |
| | | | · |
| | | | |

25.000 20.000 15.000 5.000

ES France - Département Puissance Energie 127 rue de Buzenval BP 26 - 92380 Garches

 \bigcirc

e-mail : tem@es-france.com Site Web : www.es-france.com

Equipped with Standard LAN Interface and VMCB Function

The PXT series is equipped with LAN, USB, and RS232C interfaces as standard features. By using the feature of virtual multi-channel bus (VMCB), it allows you to control remotely and monitoring for 1-to-N as well as N-to-M for large-scale networks. This feature can also be used to save communication ports or to synchronize the control timing of multiple PXT series units (up to 8 units). The PXB series manufactured by our company can also be mixed and matched for multi-channel connection.



When connecting the VMCB master unit via LAN



Schematic LAN network configuration with the PXT series

Communication monitoring function

This function monitors the communication status.

Tablet

For example, the alarm will be activated and the output will be turned off when the LAN cable is disconnected and the communication is not being confirmed within the specified time of setting. This function protects the operation from the uncontrolled condition, and it improves the system reliability.



Security for LAN connections

Access to the built-in web server can be restricted with a password. Also, when using VXI-11, HiSLIP, and SCPI-RAW for control, host restrictions can be set with the IP address. It is possible to prevent access from any terminal other than the ones registered as a host (up to 4 hosts can be registered).

• Up to 10 Units can be Operated in Parallel,

Achieving 200 kW* Intake and exhaust on the



Including master machine, up to 10 units (200 kW) can be operated in parallel. Connection is with one-control parallel operation, and the panel of the master machine can control and display the entire system. With the automatic recognition function, the need for complicated settings is eliminated, allowing the construction of high-capacity systems.

* Parallel operation is possible between models with different input rated voltages

· Please contact us if you wish to operate more than 10 units in parallel

Connection conceptual diagram Master machine machine Slave machin



Reliable and Solid Performance Even Under **High Temperatures**

Solid performance under operating temperatures of 0°C to 50°C (32 °F to 122 °F). Exhibits



Ì

Selectable Power Input

Full output at rated power regardless of input voltage. Choose from 3-phase 3-wire 200 V or 400 V models. No output limitation for either input voltage.



Safety Protection Function

- OVP (Over voltage protection)
- UVP (Under voltage protection)
- OPP (Over power protection) OCP (Over current protection)
- WDOG (Communication error protection)

Tél. 01 47 95 99 45

Fax. 01 47 01 16 22

e-mail : tem@es-france.com Site Web : www.es-france.com





Unless specified otherwise, the specifications are for the following settings and conditions. • The product is warmed up for at least 30 minutes.

The used terminology is as follows:

- TYP: These are typical values that are representative of situations where the product operates in an environment with an ambient temperature of 23 °C (73.4 °F). These values do not guarantee the
- performance of this product. setting: Indicates a setting: reading: Indicates a readout value. rating: Indicates a rated value.
- Open: Indicates equivalence to the state in which the DC OUTPUT terminals are opened. Vout: Indicates an output voltage.

Output rating

| Item | PXT20K-500 | PXT20K-1500 | |
|------------------|--------------|---------------|--|
| Rated power | 20000 W | | |
| Rated voltage *1 | 0 V to 500 V | 0 V to 1500 V | |
| Rated current *1 | ±120 A ±30 A | | |

*1. Limited by the maximum output power.

Output voltage

| Item | | PXT20K-500 | PXT20K-1500 | | | |
|---|-----------------------------|---------------------------------------|-------------|--|--|--|
| Maximum settable voltage | | 525 V | 1575 V | | | |
| Setting accuracy | | ±(0.2 % of setting + 0.1 % of rating) | | | | |
| Setting resolution | | 0.05 V | 0.1 V | | | |
| Power fluctuation *1 | | ±100 mV | ±300 mV | | | |
| Load variation *2 | | ±250 mV | ±750 mV | | | |
| Remote sensing Maximum compensation vo | Itage (reciprocating) (TYP) | 10 % of rating | | | | |
| Internal resistance setting u | upper limit | 5250 mΩ | 63000 mΩ | | | |
| Internal resistance setting r | esolution | 1 mΩ | 5 mΩ | | | |
| Response switching | | FAST, SLOW | | | | |
| | | 25 V/ms | 75 V/ms | | | |
| Slow rate owitching | | 12.5 V/ms | 37.5 V/ms | | | |
| Siew rate Switching | | 1.25 V/ms | 3.75 V/ms | | | |
| | | 0.125 V/ms | 0.375 V/ms | | | |
| Slew rate setting accuracy | | ±(20 % of setting +2.5 ms) | | | | |
| Transient response *3 | | 6 ms or less | | | | |
| p-p *5 | | 700 mV | 1750 mV | | | |
| Ripple lioise 4 | rms *6 | 100 mV | 300 mV | | | |
| Rise time *7 Full load *8 No load | | 25 ms | | | | |
| | | 25 ms | | | | |
| Fall time *0 | Full load *8 | 25 ms | | | | |
| | No load | 750 ms | | | | |

*1. 180 Vac to 252 Vac for 200 Vac input, 342 Vac to 504 Vac for 400 Vac input. At the constant load.

*2. The amount of change that occurs when the load is changed from no load to full load (rated output power/rated output voltage) with rated output voltage. The value is measured at the sensing point.

*3. The amount of time required for the output voltage to return to a value within the rated output voltage ± (0.1 % + 10 mV) when the response setting of the CV mode is FAST. The load current fluctuation is 50 % to 100 % of the maximum current with the set output voltage.

*4. In the case where the CV mode response setting is FAST and having the rated output current. Values measured using JEITA RC-9131C probe and 100:1 probe.

*5. Measurement frequency band: 10 Hz to 20 MHz

*6. Measurement frequency band: 10 Hz to 1 MHz

*7. Applicable to the case where the CV mode response setting is FAST and the rated output voltage changes from 10 % to 90 %.

*8. For a pure resistance.

*9. Applicable to the case where the CV mode response setting is FAST and the rated output voltage changes from 90 % to 10 %.

• Output current

| Item | PXT20K-500 | PXT20K-1500 | | |
|------------------------------------|---------------|---------------|--|--|
| Maximum settable current | 126 A | 31.5 A | | |
| Setting accuracy | ±(0.75 % | of rating) | | |
| Setting resolution | 0.01 A | 0.002 A | | |
| Power fluctuation | ±240 mA | ±60 mA | | |
| Load variation | ±240 mA | ±60 mA | | |
| Rise time (Short-circuit) (TYP) *1 | 25 ms | | | |
| Fall time (Short-circuit) (TYP) *2 | 5 ms | | | |
| Response switching | FAST, SLOW | | | |
| | 6 A/ms | 1.5 A/ms | | |
| Slow rate owitching (TVD) | 3 A/ms | 0.75 A/ms | | |
| Siew fate switching (11F) | 0.3 A/ms | 0.075 A/ms | | |
| | 0.03 A/ms | 0.0075 A/ms | | |
| Slew rate setting accuracy | ±(20 % of set | ting +2.5 ms) | | |

*1. In the case that the CC mode response setting is set to FAST: Applied in response to changes from 10 % to 90 % of rated output current.

*2. In the case that the CC mode response setting is set to FAST: Applied in response to changes from 90 % to 10 % of rated output current.

Output power

 \bigcirc

| Item | PXT20K-500 PXT20K-1500 | | |
|------------------------|------------------------------|-------------------------------|--|
| Maximum settable power | 21000 W | | |
| Setting accuracy *1 | ±(0.5 % of power rating + 0. | 5 % of current rating × Vout) | |

Ì

Tél. 01 47 95 99 45

Fax. 01 47 01 16 22

 \boxtimes

e-mail : tem@es-france.com

Site Web : www.es-france.com

• 200 V three-phase three-wire input Specifications for models having an input voltage rating of 200 Vac.

| Item | PXT20K-500 | PXT20K-1500 | |
|-------------------------|------------------------------------|-------------|--|
| Nominal input rating | 200 Vac to 240 Vac, 50 Hz to 60 Hz | | |
| Input voltage range | 180 Vac to 252 Vac | | |
| Input frequency range | 47 Hz to 63 Hz | | |
| Input current (MAX) *1 | 80 A (When Input voltage is 180 V) | | |
| Input power (MAX) *1 | 24 kVA | | |
| Inrush current (TYP) *2 | 90 A | | |
| Power factor (TYP) *1 | 0.96 | | |
| Output hold time | 10 ms or more | | |

*1. At the rated output power for the rated output current.

*2. Maximum peak current value when the POWER switch is turned on. (Excluding the surge current to the input filter capacitor.)

• 400 V three-phase three-wire input Specifications for models having an input voltage rating of 400 Vac.

| Item | PXT20K-500 | PXT20K-1500 | |
|-------------------------|------------------------------------|-------------|--|
| Nominal input rating | 380 Vac to 480 Vac, 50 Hz to 60 Hz | | |
| Input voltage range | 342 Vac to 504 Vac | | |
| Input frequency range | 47 Hz to 63 Hz | | |
| Input current (MAX) *1 | 40 A (When Input voltage is 342 V) | | |
| Input power (MAX) *1 | 24 kVA | | |
| Inrush current (TYP) *2 | 70 A | | |
| Power factor (TYP) *1 | 0.96 | | |
| Output hold time | 10 ms or more | | |

*1. At the rated output power for the rated output current.

*2. Maximum peak current value when the POWER switch is turned on. (Excluding the surge current to the input filter capacitor.)

Display

| Item | | PXT20K-500 | PXT20K-1500 | |
|-------------------|-----------------------------|--|---|--|
| Voltmotor | Maximum display | ±600.00 V | ±1800.00 V | |
| voitmeter | Display accuracy | ±(0.1 % of reading | + 0.2 % of rating) | |
| Ammotor | Maximum display | ±168.000 A | ±42.000 A | |
| Ammeter | Display accuracy | ±(0.75 % | of rating) | |
| Wattractor | Maximum display *1 | ±24.00 | 00 kW | |
| wallmeler | Display accuracy | Display the integrated value of voltmeter and ammeter | | |
| | Output ON / OFF | The OUTPUT LED on the | front panel lights in green | |
| | Operation mode | Indicate the followings on the upper left part of the display CV: Green CV icon CC: Red CC icon CP: Orange CP icon | | |
| | Remote (LAN) | Indicate the followings on the upper left part of the display Not connected: Red LAN icon Preparing for connection: Orange LAN icon Connected: Green LAN icon | | |
| Operation display | Alarm | Indicate the details of activated protection function on the display | | |
| | SCPI error | Indicate the error occurring at present on the display | | |
| | POWER off | Indicate residual charge warning and an instruction to turn off the display, then reboot | | |
| | Key lock | Indicate the key lock status on the upper right part of the display | | |
| | Sensing | When sensing is enabled, indicate the sensing icon on the upper right part of the display | | |
| | During parallel operation | Displaying the slave state on the slave unit | | |
| | External control | When digital input/output is enabled, indicate the | e EXT icon on the upper right part of the display | |
| | While a sequence is running | Indicate the RUN icon on the | upper right part of the display | |
| | Synchronization state | Indicate the Sync icon on the | upper right part of the display | |
| | Output delayed | Indicate a yellow mark on the upper left part of the display | | |

*1. The unit will be W if it is less than 10 kW.





Control Contro



| All alarminot requiring a rebuilt to be cleared. | ۲ | Protection specifications | LOW alarm | An alarm not requiring a reboot to be cleared. |
|--|---|---------------------------|-----------|--|
|--|---|---------------------------|-----------|--|

| liem | | | DXT20K 4500 |
|--|----------------------|--|---|
| item | | FA120R-300 FA120R-1300 | |
| | Protection operation | Output off, indicate "OVP" on the display. SLV OVP is displayed on the slave unit. | |
| OVP | Setting range | 50 V to 550 V | 150 V to 1650 V |
| (overvoltage protection) | Setting accuracy | ±(0.1 % of setting | + 0.2 % of rating) |
| | Setting resolution | 0.05 V | 0.1 V |
| | Protection operation | Output off, indicate "OCP" on the display | . SLV OCP is displayed on the slave unit. |
| OCP | Setting range | 12 A to 132 A | 3 A to 33 A |
| (overcurrent protection) | Setting accuracy | ±(0.75 % of rating) | |
| | Setting resolution | 0.01 A | 0.002 A |
| OPP | Protection operation | Output off, indicate "OPP" on the display. SLV OPP is displayed on the slave unit. | |
| | Setting range | 2 kW to 24 kW | |
| (overpower protection) | Setting accuracy | ±(1.0 % of power rating + 1.0 % of current rating × Vout) | |
| | Setting resolution | 2 W | |
| | Protection operation | Output off, indicate "UVP" on the display. SLV UVP is displayed on the slave unit. | |
| | Setting range | 0 V to 500 V | 0 V to 1500 V |
| (undervoltage protection) | Selectable | Enable/Disable | |
| (undervoltage protection) | Setting accuracy | ±(0.1 % of setting + 0.2 % of rating) | |
| | Setting resolution | 0.05 V | 0.1 V |
| | Protection operation | Output off, indicate "V | VDOG" on the display |
| Watchdog Alarm | Setting range | 1 s to 3 | 3600 s |
| | Selectable | Enable/Disable | |
| External Alarm LOW Level (external input alarm detection) | Protection operation | Output off, indicate "EXT LOW" on the display | |

• Protection Specifications HIGH alarm An alarm requiring a reboot to be cleared.

| Item | | PXT20K-500 PXT20K-1500 | |
|--|----------------------|--|--|
| Reverse Alarm (Reverse-connec- tion detection protection) | Protection operation | Output off, indicate "REVE" on the display | |
| OHP (Overheat protection) | Protection operation | Output off, indicate "OHP" on the display | . SLV OHP is displayed on the slave unit. |
| | Protection operation | Output off, indicate "LOVP" on the display | . SLV LOVP is displayed on the slave unit. |
| (Grid overvoltage protection) | Setting range | Input voltage rating 200 V Input voltage rating 400 V | ′ac model: 200 V to 258 V ′ac model: 380 V to 516 V |
| | Protection operation | Output off, indicate "LUVP" on the display | . SLV LUVP is displayed on the slave unit. |
| (Grid undervoltage protection) | Setting range | Input voltage rating 200 Vac model: 175 V or less. Input voltage rating 400 Vac model: 333 V or less. | |
| Line Frequency Error (Grid abnor- | Protection operation | Output off, indicate "FREQ" on the display. SLV FREQ is displayed on the slave unit. | |
| mal frequency protection) | Detection value | 42 Hz/68 Hz | |
| External Alarm HIGH Level (External input alarm detection) | Protection operation | Output off, indicate "EXT HIGH" on the display | |
| Parallel Communication Error (Parallel operation communication error detected) | Protection operation | Output off, indicate "PARA COM" on the display | |
| Para Other Slave Alarm (Parallel operation slave error occurred) | Protection operation | Output off, indicate "SLV OTHR" on the display | |
| Incorrect Slave Alarm (Not applicable device connected) | Protection operation | Output off, indicate "SLV INC" on the display | |
| Too many connections (Too many parallel connections) | Protection operation | Output off, indicate "TOO MANY" on the display | |
| Hardware ERR *1 (Hardware error) | Protection operation | Output off, indicate "ERRH" on the display | A. SLV ERRH is displayed on the slave unit. |
| Software ERR *2 (Software error) | Protection operation | Output off, indicate "ERRS" on the display. SLV ERRS is displayed on the slave unit. | |

to occurs when an abnormality related to the hardware is detected and the internal unit comes to an emergency stop.
 It occurs when an abnormality related to the software is detected and the internal unit comes to an emergency stop.

• External analog I/O

| Item | | | PXT20K-500 | PXT20K-1500 |
|---------|---|---------------------|---|-------------|
| | Input points | | 2 points | |
| | Voltage (CV) external | Setting range | 0 % to 100 % of the rated output voltage | |
| | | Input voltage range | 0 V to +5 V or 0 V to +10 V (Selectable) | |
| Input | voltage control | Accuracy | ±(1 % of rating) | |
| | Current (CC) external voltage control, power (CP) external voltage control *1 | Setting range | 0 % to 100 % of the rated current and rated power | |
| | | Input voltage range | 0 V to +5 V or 0 V to +10 V (Selectable) | |
| • | | Accuracy | ±(1 % o | f rating) |
| | Output points | | 2 po | ints |
| Outrast | | Output range | 0 % to 100 % of the rated output voltage | |
| Output | Voltage monitor (VMON) Current monitor (IMON) | Output voltage | 0 V to 5 V or 0 V to 10 V (Selectable) | |
| | | Accuracy | ±(1 % o | f rating) |

 Tél. 01 47 95 99 45

 Fax. 01 47 01 16 22

e-mail : tem@es-france.com

Site Web : www.es-france.com

 \boxtimes

*1. Select either current control or power control.



• External digital input

| Item | | PXT20K-500 | PXT20K-1500 | |
|--|--|---|--|--|
| Fixed input points 1 point (Polarity switchable) | | ity switchable) | | |
| Selected input points | | 5 points (Polarity switchable) | | |
| Input form | rm Photocoupler isolated input (Applicable to both current sink / source output) | | le to both current sink / source output) | |
| Fixed function | ALARM IN | HIGH alarm occurrence | | |
| | OFF | Do not use | e terminals | |
| | OUTPUT ON | Turn on t | he output | |
| | OUTPUT OFF | Turn off t | Turn off the output | |
| | OUTPUT CTRL | Turn on of off the output | | |
| | L ALARM IN | LOW alarm occurrence | | |
| | ALARM CLR | LOW alarm clearance | | |
| Solocting function | SEQ RUN | Sequence start/end | | |
| Selecting function | SEQ PAUSE | Sequence pause/resume | | |
| | SEQ TRIG IN | Input the trigger for sequence | | |
| | ACQUIRE TRIG | Input the measurement trigger | | |
| | MEM1 RECALL | Recall prese | et memory 1 | |
| | MEM2 RECALL | Recall prese | et memory 2 | |
| | INTEG CTRL | Starting/stopping integration measurement | | |
| | INTEG RESET | Resetting integration | n measurement data | |
| External circuit power supply range 12 V to 24 Vdc (±10 %) | | Vdc (±10 %) | | |

• External digital output

| Item | | PXT20K-500 | PXT20K-1500 | |
|--------------------|---------------------------------------|--|---|--|
| Output points | | 6 points (Polarity switchable) | | |
| Output form | utput form Semiconductor relay output | | or relay output | |
| OFF | | Do not use | e terminals | |
| | OUTPUT ON | Outputting the signal | while the output is ON | |
| | POWER ON | Signal is output when power su | pply is on and output is possible | |
| | H ALARM OUT | Output a signal when a HIGH alarm occurs | | |
| | L ALARM OUT | Output a signal when a LOW alarm occurs | | |
| | CC STATUS | Output a signal when operating in the CC mode | | |
| Selecting function | CV STATUS | Output a signal when operating in the CV mode | | |
| | SEQ STATUS | Output the trigger for sequence | | |
| | SEQ TRIG OUT | Signal is output while the sequence is running | | |
| | EXT DIN BUSY | Output a signal when the digital input is in BUSY status | | |
| | MEM1 ACT TIME | Signal is output when the setting is completed for preset memory 1 | | |
| | MEM2 ACT TIME | Signal is output when the setting | is completed for preset memory 2 | |
| | RELAY DRIVE | Output a signal after approx. 100 ms in step with on/off of the DC | Output a signal after approx. 100 ms in step with on/off of the DC OUTPUT terminal output. You can set this parameter to only Ch.6. | |

Panel Explanation



 \boxtimes Site Web : www.es-france.com

• Communication specifications

| Item | | PXT20K-500 | PXT20K-1500 |
|--------------------------|----------------------------|---|----------------------|
| Common Software protocol | | IEEE std. 488.2-1992 | |
| specifications | Command language | Complies with SCPI | Specification 1999.0 |
| RS232C | Hardware | D-SUB 9-pin connector Baud rate: 1200, 2400, 4800, 9600, 19200, 38400, 57600, 115200 bps Data length: 8 bits, Stop bits: 1 bit, Parity bit: None Flow control: No, CTS-RTS | |
| | Program message terminator | LF during reception, LF during transmission | |
| | Hardware | Standard type B socket, Complies with the USB 2.0 specifications; data rate: 480 Mbps (high speed) | |
| USB (device) | Program message terminator | LF or EOM during reception, LF + EOM during transmission | |
| | Device class | Complies with the USBTMC-USB488 device class specifications | |
| USB (host) | Hardware | Standard type A socket, Complies with the USB 2.0 specifications; data rate: 480 Mbps (high speed) | |
| | Hardware | IEEE 802.3 100BASE-TX or 10BASE-T Ethernet | |
| | Communication protocol | SCPI-RAW, SCPI-Telnet, HiSLIP, VXI-11 | |
| LAN | Program message terminator | SCPI-RAW: LF during reception, LF during transmission HiSLIP: LF or END during reception, LF + END during transmission | |
| | Compliant standards | LXI Version 1.5 Specifications 2016 | |

Others

| Item | | | PXT20K-500 | PXT20K-1500 | |
|-------------------------|---|--------------------|---|--|--|
| Currentian function | Overview | | SYNC icon is displayed on the display when synchronization is established with the internal clock after connecting with other PXT series using the EXT SYNC connector. | | |
| (clock synchronization) | Sequence synchronization | | Synchronization of the program start and step start | | |
| (olocit dynomication) | Measurement | synchronization | Synchronization of the | he measurement start | |
| | Output synchro | onization | Synchronization | of output ON/OFF | |
| | Operation mod | le | CV, CC, an | id CP modes | |
| | Maximum num | ber of programs | 3 | 30 | |
| Sequence function | Maximum num | ber of steps | 10 | 000 | |
| | Step execution | time | 1 ms to 3 | 3600000 s | |
| | Loop count | | 1 to 10000 | I0, or infinite | |
| Output-on/off delay | Setting range | | 0.0 s to | o 99.9 s | |
| function | Setting resolut | ion | 0. | .1 s | |
| Over current protection | Setting range | | 1 ms to | 2000 ms | |
| (OCP) delay function | Setting resolut | ion | 1 | ms | |
| Multichannel (VMCB) | Connection be unit and a PC | tween the master | LAN, USE | B, RS232C | |
| Turiction | Connection with | th slave units | L | AN | |
| | Measurement start condition (trigger source) | | Conditions for starting me (when inputting from display, when inputting commands by re when operating in | asurement can be selected remote control, when inputting signals by external control, and n synchronization) | |
| | Number of mea | asurements | 1 to 6 | 65536 | |
| Magazinamant triagan | Measurement | Setting range | 0 s to | 0 100 s | |
| measurement trigger | delay time | Setting resolution | 0.1 | l ms | |
| | Measurement | Setting range | 0.1 ms t | to 3600 s | |
| | interval | Setting resolution | 0.1 ms | | |
| | Measurement | Setting range | 0.1 m | is to 1 s | |
| | time Setting resolution | | 0.1 ms | | |
| I-V characteristic | Operation mod | le | CV/CC | C mode | |
| function | Number of set | up items | 3 to 100 items (interpolated be | etween points with straight lines) | |
| Preset value | Number of me | nory entries | 2 | 20 | |
| Memory | Saved setting | | Values in CV, CC, and CP modes, protection function | n values, IR values, bleeder, and output delay setting. | |
| | Number of me | nory entries | 2 | 21 | |
| Setup Memory | Saved setting | | On/off of the output from Output voltage value/Output c. Outpu Resp Slew Priority operation mode (f Ble Outpu Number of I-V cha Internal resist Over voltage protect Over current prote Over current prote Over current prote Over over protect Over current prote Over power pr Line overvoltage pr Measurement trigger settings (So Integration settin | the DC OUTPUT terminal urrent value/Output power value it mode ponse v Rate Priority when output is ON) eder it delay aracteristics (Count) ance value (IR) protection (OVP) cion (UVP, UVP Enable) action (OCP, Delay) rotection (OPP) rotection (CPP) protection (Line OVP) purce, Count, Delay, Enable, Timer) ngs (Gate, Reset) | |
| | Level 1 | | Output on/off and preset n | nemory recall are available | |
| Key Lock | Level 2 | | Output on/off | f are available | |
| | 1 | | | | |

 Tél. 01 47 95 99 45

 Fax. 01 47 01 16 22

e-mail : tem@es-france.com

Site Web : www.es-france.com

 \bowtie

 \bigcirc

| General spe | cifications | | | |
|--|------------------------------|---|-------------------------------------|--|
| Item | | PXT20K-500 | PXT20K-1500 | |
| Weight | | Approx. 38 kg (83.78 lbs) | Approx. 37 kg (81.57 lbs) | |
| Dimensions 430 (16.93)(MAX455 (17.91))W×128 (5.04)(MAX160 (6.30))H×720 (28.35)(MAX980 (38.58)) Refer to Outline Drawing | | 30))H×720 (28.35)(MAX980 (38.58))Dmm(mm (inches)) line Drawing | | |
| Operating environment | | Indoor use, Overv | Indoor use, Overvoltage category II | |
| | Operating temperature | 0 °C to +50 °C (3 | 32 °F to +122 °F) | |
| Environmental | Operating humidity | 20 % rh to 85 % rh | (no condensation) | |
| conditions | Storage temperature | -25 °C to +60 °C (| -13 °F to +140 °F) | |
| | Storage humidity | 90 % rh or less (r | no condensation) | |
| | Altitude | Up to 2 | 2000 m | |
| Cooling system | Forced air cooling using fan | | ling using fan | |
| Accessories | | AC INPUT terminal cover, External control connector kit (1 set), Chassis connection wire, DC OUTPUT terminal cover, DC OUTPUT terminal screws (1 pair), EXT SYNC connector cover, SENSING connector cover, SENSING connector (2 pieces), Synchronized operation signal cable kit, Safety Information (1 copy), China RoHS sheet (1 copy), Getting Started Guide (1 copy), Heavy object warning label (1 piece) | | |
| | Between input and GND | 2000 V/co for 1 minuto | | |
| voltage | Between input and output | 2200 Vac 1 | | |
| voltage | Between output and GND | 1800 Vdc for 1 minute | 3000 Vdc for 1 minute | |
| Insulation | Between input and GND | 30 ΜΩ, | 500 Vdc | |
| resistance | Between input and output | 30 MΩ, 1000 Vdc | | |
| Isolation voltage ±1000 V | | +2000 V/-1000 V | | |
| Electromagnetic compatibility (EMC) *1 *2 | | Complies with the requirements of the following directive and standards. EMC Directive 2014/30/EU EN 61326-1 (Class A *3) | | |
| Safety *1 | | Complies with the requirements of the following directive and standards. Low Voltage Directive 2014/35/EU *2 EN 61010-1 (Class I *4, Overvoltage category II, Pollution Degree 2 *5) | | |

*1. Does not apply to specially ordered or modified products.

*2. Only for models with CE marking / UKCA marking on their body.

*3. This is a Class A instrument. This product is intended for use in an industrial environment. This product may cause interference if used in residential areas. Such use must be avoided unless the user takes special measures to reduce electromagnetic emissions to prevent interference to the reception of radio and television broadcasts.

This is a Class I instrument. Be sure to ground this product's protective conductor terminal. The safety of this product is guaranteed only when the product is properly grounded.
 Pollution is addition of foreign matter (solid, liquid or gaseous) that may produce a reduction of dielectric strength or surface resistivity. Pollution Degree 2 assumes that only non-conductive pollution will occur except for an occasional temporary conductivity caused by condensation.

• Outline drawing *Maximum dimensions include protrusions and accessory covers.



C

Unit: mm (inches)

 \bowtie

* The number of bus bars varies depending on the model.

 \bigcirc

Tél. 01 47 95 99 45 Fax. 01 47 01 16 22

Ordering Information

• Example of 100 kW system configuration (1500 V)

| Product name | Model name | Volume |
|--|-------------|--------|
| High-capacity wide-range DC power supply | PXT20K-1500 | 5 |
| Parallel operation cable | PC01-PXB | 4 |
| Rack mount bracket | KRB3-TOS | 5 |

• Example of 200 kW system configuration (1500 V)

| Product name | Model name | Volume |
|--|-------------|--------|
| High-capacity wide-range DC power supply | PXT20K-1500 | 10 |
| Parallel operation cable | PC01-PXB | 9 |
| Rack mount bracket | KRB3-TOS | 10 |

* Rack for mounting PXT main unit, power cables for 3-phase input, and load cables available separately. * We can rack up the system and provide as a customer-specific solution. (Sold separately)

Options

- Parallel operation signal cable kit PC01-PXB (Cable length: 1.5 m)
- Rack mount bracket
 KRB3-TOS (EIA inch rack standard)
 KRB150-TOS (JIS millimeter rack standard)

Load cable

| Model name | Length | Maximum allowable current | Terminal size | Applicable models |
|------------------|--------|---------------------------|---------------|-------------------|
| DC80-2P3M-M10M10 | - 3 m | 200 A | M10/M10 | PXT20K-500 |
| HV22-2P3M-M12M8 | | 80 A | M12/M8 | PXT20K-1500 |

• Three-phase input power cord *The switchboard ends of the power cords have not been prepared for connection.

| Model name | Length | Nominal cross-sectional area | Terminal size | Applicable models |
|------------------|--------|------------------------------|---------------|-------------------|
| AC22-4P3M-M6C-4S | 3 m | 22 mm ² | M6 | All models |

