

RFLUPA250K220MA

Wide Band Power Amplifier 250KHz~220MHz

Compliant



Features

- Wide Band Power Amplifier
- Small Signal Open loop Gain: 60 dB
- Output Power: 150W CW •

Typical Applications

- Test and Measurement
- Wireless Communications
- Military and Aerospace

Electrical Specifications, 1 _A = +25									
Parameter		Min.	Тур.	Max.	Units				
Frequency Range		0.25		220	MHz				
Open Loop Gain (ALC Open I	Loop)		60		dB				
Gain Flatness (ALC Closed L	oop)		±2.5		dB				
Gain Adjustment Range (ALC Clo	sed Loop)		15		dB				
Display Power Value Erro	or		±2.5	±3.5	dBm				
Maximum Output Power (Input to odE	52	53		dBm					
Output Third Order Intercept (IP3) @Ou		56		dBm					
Input VSWR			1.5	2	:1				
Harmonic Suppression @Pout		-15	-12	dBc					
Efficiency	50	55		%					
DCV/slipses	@24V		0.7	1	А				
DC voitage	@48V		6	8	А				
Input / Output Connecto	SMA-Female								



RFLUPA250K220MA

Environmental Specifications and Test Standards

Parameter	Standard	Description					
Operational Temperature		-20°C~+50°C					
Storage Temperature		-50°C~+105℃					
Thermal Shock		1 Hour@ -45℃ → 1 Hour @ +85℃ (5 Cycles)					
Random Vibration		Acceleration Spectral Density 6 (m/s) Total 92.6 RMS					
Electrical & Temperature Burn In	MIL-STD-39016	Temperature +85°C for 72 Hours					
Shock		 Weight >20g, 50g half sine wave for 11ms, Speed variation 3.44m/s Weight <=20g, 100g Half sine wave for 6ms, Speed variation 3.75m/s Total 18 times (6 directions, 3 repetitions per direction). 					
Altitude		Standard: 30,000 Ft (Epoxy Sealed Controlled Environment) Optional: Hermetically Sealed (60,000 ft. 1.0 PSI min)					
Hermetically Sealed (Optional)	MIL-STD-883	MIL-STD-883 (For Hermetically Sealed Units)					

Amplifier Use

Ensure that the amplifier input and output ports are safely terminated into a proper 50 ohm load before turning on the power. Never operate the amplifier without a load. A proper 50 ohm load is defined as a load with impedance less than 1.9:1 or return loss larger than 10dB relative to 50 Ohm within the specified operating band width.

Power Supply Requirements

Power supply must be able to provide adequate current for the amplifier. Power supply should be able to provide 1.5 times the typical current or 1.2 times the maximum current (whichever is greater).

In most cases, RF - Lambda amplifiers will withstand severe mismatches without damage. However, operation with poor loads is discouraged. If prolonged operation with poor or unknown loads is expected, an external device such as an isolator or circulator should be used to protect the amplifier.

Ensure that the power is off when connecting or disconnecting the input or output of the amp.

Prevent overdriving the amplifier. Do not exceed the recommended input power level.

Adequate heat-sinking required for RF amplifier modules. Please inquire.

Amplifiers do not contain Thermal protection, Reverse DC polarity or Over voltage protection with the exception of a few models. Please inquire.

Proper electrostatic discharge (ESD) precautions are recommended to avoid performance degradation or loss of functionality.

What is not covered with warranty?

Each RF - Lambda amplifier will go through power and temperature stress testing. Since the die, ICs or MMICs are fragile, these are not covered by warranty. Any damage to these will NOT be free to repair. lide Band Power Amplifier 250KHz~220MHz



RFLUPA250K220MA

Module Interface and Description

1. Power Input Interface: +24V&48V Input Interface



Power Input Interface Table

Pin Number	Definition
A1	+24V
A2	GND
A3	+48V

2. RF Output: Power Amplifier Output Interface.

Test Data

Signal Source	Frequency	250K	500K	1M	5M	10M	20M	40M	80M	120M	160M
odBm	Display dBm	51.2	51.5	50.2	52.3	53.2	55.0	54.8	53.8	52.8	52.6
	Actual Measurement dBm	52.3	52.3	52.3	53.2	53.2	53.3	52.9	52.4	52.3	52.1
The typical value of neuror test when input is odPm, attenuator 6 odP and output is sodPm (maximum)											

The typical value of power test when input is odBm, attenuator 6odB and output is 53dBm (maximum): spectrum analyzer MS8609A.

Harmonic	Frequency	250K	500K	1M	5M	10M	20M	40M	80M	120M	160M
dBc	Two Times	25	23.5	23.1	25.2	24.9	27.9	28.6	30.3	32.4	36.4
	Three times	21	21.6	21.1	24.3	20.1	19	17.5	25.3	27	29.6
he typical value of harmonic test is input when odBm, attenuator 6odB and output is 50.8dBm (120W):											

spectrum analyzer MS8609A.



RF-LAMBDA LEADER OF RF BROADBAND SOLUTIONS

RFLUPA250K220MA

Outline Drawing:

All Dimensions in mm [inches]



Important Notice

The information contained herein is believed to be reliable. RF-Lambda makes no warranties regarding the information contained herein. RF-Lambda assumes no responsibility or liability whatsoever for any of the information contained herein. RF-Lambda assumes no responsibility or liability whatsoever for the use of the information contained herein. The information contained herein is provided "AS IS, WHERE IS" and with all faults, and the entire risk associated with such information is entirely with the user. All information contained herein is subject to change without notice. Customers should obtain and verify the latest relevant information before placing orders for RF-Lambda products. The information contained herein or any use of such information does not grant, explicitly or implicitly, to any party any patent rights, licenses, or any other intellectual property rights, whether with regard to such information itself or anything described by such information. RF-Lambda products are not warranted or authorized for use as critical components in medical, life-saving, or life sustaining applications, or other applications where a failure would reasonably be expected to cause severe personal injury or death.