

Arbitrary/Function Generator

AFG1000 Series Datasheet



The AFG1000 Series Arbitrary Function Generator provides a waveform generation tool with the best price performance ratio. It includes two models with dual channels, up to 60 MHz bandwidth and up to 10 V_{p-p} output amplitude. The four run modes, 50 built-in frequently-used waveforms and the built-in 200 MHz frequency counter cover most waveform generation needs in your experiment and test jobs. The 3.95-inch TFT LCD, short-cut buttons, USB interface and PC software provide the most intuitive ways to configure the instrument.

Key performance specifications

- Dual-channel, 25 MHz or 60 MHz sine waveforms, 12.5 MHz or 30 MHz square waveforms
- 14 bits, 125 MS/s or 300 MS/s arbitrary waveforms with 8 k points or 1 M points record length
- Amplitude 1 mV_{p-p} to 10 V_{p-p} into 50 Ω loads

Key features

- Continuous, sweeping, burst, and modulation modes (AM, FM, PM, ASK, FSK, PSK, PWM) covers most requirements for students and other users to get the experiments/test job done
- 64-MByte internal non-volatile memory for arbitrary waveform storage
- Built-in 200 MHz counter with 6-digit resolution offers an easy and precise way of frequency/period/pulse width/duty cycle measurement
- Standard USB host/device for memory expansion and remote control
- Free ArbExpress makes user defined waveforms editing extremely easy

- Compatible with TekSmartLab™ for easy teaching and learning
- Standard 5-year warranty

Applications

- Electric and electronics experiments
- Communications experiments
- Sensor simulation
- Functional test

Performance and features

1 μHz to 25 MHz or 60 MHz sine waveform range, with 12-digit or 1 μHz resolution and a ±1 ppm drift high stability time base, provides great signal fidelity in the frequency domain. With 1 mV_{p-p} to 10 V_{p-p} output amplitude range, and 14-bit or 1 mV_{p-p} resolution over the whole frequency range, there is no need to compromise between output amplitude and frequency any more.

Four different run modes cover most use cases with a cost effective solution. 50 most-frequently used standard and arbitrary waveforms are built-in for easy access. Up to 1 M points arbitrary waveforms memory enables users to replicate real world signals captured with a Tektronix oscilloscope or defined with ArbExpress. The built-in 200 MHz and 6-digit resolution frequency counter is an easy and precise way to measure frequencies/periods/pulse widths/duty cycles.

Ease of use

The high-resolution 3.95-inch color TFT display shows relevant settings and parameters in both text and graphic formats, which give users full confidence in their settings, and let them focus on the task at hand. The front panel shortcut buttons and rotary knob make accesses to most frequently used functions and settings with minimum effort and time. The built-in 64-MByte non-volatile memory together with USB stick memory interface, provide unlimited space for user-defined waveform storage.

Software and solutions

Compatible with ArbExpress, the user-defined arbitrary waveforms generated by the free software can be loaded on the AFG1000 easily with a USB memory stick.

As a building block of Tektronix educational solution, the AFG1000 can be embedded into TekSmartLab and enable a cost efficient and effective way of teaching, learning, and lab management.

Specifications

All specifications apply to all models unless noted otherwise.

Channels

Number of channels	2
--------------------	---

Built-in waveforms

Built-in waveforms	Sine, Square, Pulse, Ramp, Noise, and 45 frequently used arbitrary waveforms
--------------------	--

General characteristics

Sine waves

	AFG1022	AFG1062
Range	1 μ Hz to 25 MHz	1 μ Hz to 60 MHz
Sine wave in burst mode	2 MHz to 25 MHz	2 MHz to 30 MHz
Effective maximum frequency out	25 MHz	60 MHz
Amplitude flatness (1 V_{p-p}), typical		
<10 MHz	± 0.2 dB	± 0.2 dB
≥ 10 MHz	± 0.3 dB	± 0.3 dB
Harmonic distortion (1 V_{p-p})		
≤ 10 MHz	< -50 dBc	< -60 dBc
>10 MHz	< -50 dBc	< -47 dBc
Total harmonic distortion	< 0.2% (10 Hz to 20 kHz, 1 V_{p-p})	
Spurious (1 V_{p-p})	< -45 dBc	
Phase noise, typical	1 MHz: < -110 dBc/Hz at 10 kHz offset, 1 V_{p-p}	
Residual clock noise, typical	-57 dBm	

Square wave

	AFG1022	AFG1062
Range	1 μ Hz to 12.5 MHz	1 μ Hz to 30 MHz
Rise/fall time	<12 ns	<10 ns
Jitter (rms), typical	<1 ns	<500 ps
Overshoot	<5%	

Ramp wave

	AFG1022	AFG1062
Range	1 μ Hz to 1 MHz	1 μ Hz to 2 MHz
Linearity, typical	$\leq 0.1\%$ of peak output at 10% - 90% of amplitude range, at 1 kHz, 1 V_{p-p} , 50% symmetry	
Symmetry	0.0% to 100.0%	

General characteristics

Pulse wave

	AFG1022	AFG1062
Range	1 μ Hz to 12.5 MHz	1 μ Hz to 30 MHz
Pulse width range	40 ns to 999 ks	17 ns to 999 ks
Pulse width resolution	1 ns or 4 digits	
Pulse duty	<1 MHz, 0.1% to 99.9% (limitations of pulse duty width apply)	
	\geq 1 MHz, 50% fixed	\geq 1 MHz, 50% fixed
Edge transition time	<12 ns, fixed	<10 ns, fixed
Overshoot, typical	<5%	
Jitter (rms), typical	<1 ns	<500 ps

Noise

	AFG1022	AFG1062
Noise bandwidth (-3 dB)	25 MHz	50 MHz
Noise type	White Gaussian	

DC

	AFG1022	AFG1062
Range	-5 V to +5 V, 50 Ω load	
	-10 V to +10 V, open circuit or high Z load	

Arbitrary waveform

	AFG1022	AFG1062
Range	1 μ Hz to 10 MHz	1 μ Hz to 30 MHz
Arbitrary waveform in burst mode	2 mHz to 10 MHz	2 mHz to 30 MHz
Effective analog bandwidth (-3 dB)	30 MHz	60 MHz
Non-volatile memory	64 MByte	
Memory		
Length	2 to 8,192	2 to 1 M-point
Sampling rate	125 MS/s	300 MS/s
Vertical resolution	14 bits	
Rise and fall time	< 10 ns	< 8 ns
Jitter (rms), typical	< 6 ns	

Frequency

	AFG1022	AFG1062
Resolution	1 μ Hz or 12 digits	
Internal reference stability	\pm 1 ppm at 0 - 40 $^{\circ}$ C	
Internal reference aging	\pm 1 ppm per year	

General characteristics

Amplitude

Range (50 Ω load)

≤ 25 MHz

> 25 MHz

AFG1022	AFG1062
1 mV _{p-p} to 10 V _{p-p}	1 mV _{p-p} to 10 V _{p-p}
-	1 mV _{p-p} to 5 V _{p-p}

Range (Open circuit or high Z load)

≤ 25 MHz

> 25 MHz

2 mV _{p-p} to 20 V _{p-p}	2 mV _{p-p} to 20 V _{p-p}
-	2 mV _{p-p} to 10 V _{p-p}

Accuracy

$\pm(1\% \text{ of setting} + 1 \text{ mV}_{p-p})$, (1 kHz sine waveform, 0 V offset)

Resolution

1 mV_{p-p}, 1 mV_{rms} or 4 digits

Units

V_{p-p}, V_{rms}

Output impedance

50 Ω (typical)

Local impedance setting

Selectable: 50 Ω , 1 Ω to 10.000 k Ω , High Z (adjusts displayed amplitude according to selected load impedance)

Isolation

No floating ground, signal ground connected to chassis ground

Signal output protection

Short-circuit tolerance, main output automatically disabled when over current

DC offset

Range

$\pm(5 V_{pk} - \text{Amplitude}_{p-p}/2)$, 50 Ω load
 $\pm(10 V_{pk} - \text{Amplitude}_{p-p}/2)$, open circuit or high Z load

Accuracy

$\pm(1\% \text{ of } |\text{setting}| + 1 \text{ mV} + 0.5\% \text{ of amplitude } (V_{p-p}))$

Resolution

1 mV or 4 digits

Modulation

Modulation, sweeping, and burst modes are only available for channel 1 on the AFG1022.

The AFG1062 supports equal strong channels with modulation, sweeping, and burst modes.

Amplitude modulation

Carrier waveforms

Sine, square, ramp, arbitrary, except DC and noise

Source

Internal / external

Internal modulating waveforms

Sine, square, ramp, noise, arbitrary

Internal AM frequency

2 mHz to 20 kHz

Depth

0.0% to 100.0%

Frequency modulation

Carrier waveforms

Sine, square, ramp, arbitrary, except DC and noise

Source

Internal / external

Internal modulating waveforms

Sine, square, ramp, noise, arbitrary

Modulation

Internal modulating frequency 2 mHz to 20 kHz
Frequency deviation (limited by carrier waveform type)

AFG1022	AFG1062
2 mHz to 12.5 MHz	2 mHz to 30 MHz

Phase modulation

Carrier waveforms Sine, square, ramp, arbitrary, except DC and noise
Source Internal / external
Internal modulating waveforms Sine, square, ramp, noise, arbitrary
Internal PM frequency 2 mHz to 20 kHz
Phase Deviation 0° to 180°

Amplitude shift keying

(AFG1062 only)
Carrier waveforms Sine, square, ramp, arbitrary, except DC and noise
Source Internal / external
Internal modulating waveforms 50% duty cycle square
ASK rate 2 mHz to 100 kHz

Frequency shift keying

Carrier waveforms Sine, square, ramp, arbitrary, except DC and noise
Source Internal / external
Internal modulating waveforms 50% duty cycle square
FSK rate 2 mHz to 100 kHz

Phase shift keying

(AFG1062 only)
Carrier waveforms Sine, square, ramp, arbitrary, except DC and noise
Source Internal / external
Internal modulating waveforms 50% duty cycle square
PSK rate 2 mHz to 100 kHz

Pulse width modulation

(AFG1062 only)
Carrier waveforms Pulse, ≤1 MHz
Source Internal / external
Internal modulating waveforms Sine, square, ramp, arbitrary, except DC and noise
PWM frequency 2 mHz to 20 kHz
Deviation 0.0% to 50.0% of pulse period

Sweeping

Modulation, sweeping, and burst modes are only available for channel 1 on the AFG1022.

The AFG1062 supports equal strong channels with modulation, sweeping, and burst modes.

Carrier waveforms	Sine, square, ramp, arbitrary (AFG1062 only)	
Minimum start-stop frequency	1 μ Hz	
Maximum start-stop frequency		
Sine	AFG1022	AFG1062
	25 MHz	60 MHz
Square	12.5 MHz	30 MHz
Ramp	1 MHz	2 MHz
Type	Linear, logarithmic	
Direction	Up / down	
Sweep time	1 ms to 500 s \pm 0.1%	
Trigger sources	Internal, external, or manual	

Burst

Modulation, sweeping, and burst modes are only available for channel 1 on the AFG1022.

The AFG1062 supports equal strong channels with modulation, sweeping, and burst modes.

Waveforms	Sine, square, ramp, pulse, arbitrary except DC and noise
Types	AFG1022: count (1 to 50,000 cycles), infinite, gated AFG1062: count (1 to 1,000,000 cycles), infinite, gated
Start phase	-360° to +360°
Trigger sources	Internal, external, or manual
Internal trigger interval	(40 ns or (cycles x period) to 500 s) \pm 1%
Gate source	External trigger

Frequency counter

Function	Frequency, period, positive pulse width, duty cycle
Frequency range	100 mHz to 200 MHz
Frequency resolution	6 digits
Coupling mode	AC, DC

Frequency counter

Voltage Range and Sensitivity, DC coupled (non-modulation signal)

100 mHz to 100 MHz	250 mV _{p-p} to 5 V _{p-p} (AC + DC)
100 MHz to 200 MHz	450 mV _{p-p} to 3 V _{p-p} (AC + DC)

Voltage range and sensitivity, AC coupled (non-modulation signal)

1 Hz to 100 MHz	250 mV _{p-p} to 5 V _{p-p}
100 MHz to 200 MHz	450 mV _{p-p} to 4 V _{p-p}

Pulse width and duty cycle measure	1 Hz to 10 MHz
------------------------------------	----------------

Input impedance	1 M Ω in parallel with 100 pF
-----------------	--------------------------------------

High frequency noise restraint (HFR)	On / Off (HFR frequency = 500 kHz)
--------------------------------------	------------------------------------

Sensitivity	Low, middle, or high
-------------	----------------------

Trigger level range	-2.5 V to +2.5 V
---------------------	------------------

Auxiliary inputs and outputs

External modulation input

Input frequency range	DC to 20 kHz
Input voltage range	All except FSK: ± 1 V full scale, FSK: 3.3 V logic level
Input impedance	12 k Ω (typical)

External trigger input

Level	TTL-compatible
Slope	Rising or falling (selectable)
Pulse Width	>100 ns

External reference clock input

Impedance	400 Ω , AC coupled
Requested Input voltage swing	100 mV _{p-p} to 5 V _{p-p}
Locking range	10 MHz \pm 9 kHz

External reference clock output

Frequency	10 MHz
Impedance	50 Ω , DC coupled
Amplitude	1.6 V _{p-p} into 50 Ω load

Communication interface

USB	Host and device, USB TMC compliance
-----	-------------------------------------

Display

Display type	3.95-inch
Display resolution	480 by 320
Display colors	65,536

Menu and online help languages

Menu and online help languages	English and Simplified Chinese
--------------------------------	--------------------------------

Power source

Supply	220-240 VAC, 100-120 VAC, 50/60 Hz, CAT II
Consumption	AFG1022: Less than 28 W AFG1062: Less than 35 W
Fuse	110 V: 250 V, F1AL 220 V: 250 V, F0.5AL
Warm-up time	30 minutes (typical)

Physical characteristics

Dimensions (W, H, D)	230 × 110 × 306 mm (9.0 × 4.4 × 12.1 in)
Weight	
Net	3.4 kg (7.5 lbs)
Shipping	4.7 kg (10.3 lbs)

EMC environment and safety

Temperature	
Working	0 °C to 40 °C (32 °F to 104 °F)
Storage	-20 °C to 60 °C (-4 °F to 144 °F)
Relative humidity (non-condensing)	Operating: ≤ 80%, +0 °C to +40 °C (+32 °F to +104 °F) Non-operating: 5% to 90%, < +40 °C (+104 °F) Non-operating: 5% to 80%, ≥ +40 °C (+104 °F) to ≤ +60 °C (+140 °F)
Altitude	Operating: up to 3,000 m (9843 ft.) Non-operating: up to 12,000 m (39,370 ft)
Cooling method	Fan cooling
EMC compliance	
European Union	EN 61326-1
Australia/NZ	CISPR 11, Class A

EMC environment and safety

- Safety compliance
 - UL 61010-1
 - CAN/CSA-C22.2 No. 61010-1
 - EN 61010-1
 - IEC 61010-1
-

Ordering information

Models

AFG1022	Arbitrary Function Generator
AFG1062	Arbitrary Function Generator

Instrument options

Power plug options

Opt. A0	North America power plug (115 V, 60 Hz)
Opt. A1	Universal Euro power plug (220 V, 50 Hz)
Opt. A2	United Kingdom power plug (240 V, 50 Hz)
Opt. A3	Australia power plug (240 V, 50 Hz)
Opt. A5	Switzerland power plug (220 V, 50 Hz)
Opt. A6	Japan power plug (100 V, 50/60 Hz)
Opt. A10	China power plug (50 Hz)
Opt. A11	India power plug (50 Hz)
Opt. A12	Brazil power plug (60 Hz)
Opt. A99	No power cord

Service options

Opt. C3	Calibration Service 3 Years
Opt. C5	Calibration Service 5 Years

Probes and accessories are not covered by the warranty and Service Offerings. Refer to the datasheet of each probe and accessory model for its unique warranty and calibration terms.

Accessories

Standard Accessories

- AFG1000 Arbitrary/Function Generator Safety and Compliance Instructions; printed document
- AFG1000 Documentation CD containing the following PDF documents:
 - AFG1000 Arbitrary/Function Generators Quick Start User Manual, English
 - AFG1000 Arbitrary/Function Generators Quick Start User Manual, Simplified Chinese
 - AFG1000 Arbitrary/Function Generators Programmer Manual
 - AFG1000 Arbitrary/Function Generators Specifications and Performance Verification Manual
- PDF documents not included on the AFG1000 Documentation CD but available for download from www.tektronix.com.
 - AFG1000 Arbitrary/Function Generators Quick Start User Manual, Russian, (Tektronix part number 077-1135-xx)
 - AFG1000 Arbitrary/Function Generators Quick Start User Manual, Japanese, (Tektronix part number 077-1166-xx)
- Packing list
- Power cord, specified by country
- Certificate of calibration; printed document
- USB cable x 1, Type A to Type B
- BNC cable x 2
- Tektronix Supplemental Information Sheet For the Peoples Republic of China: China RoHs; printed document
- Fuse, cartridge; 5 x 20 mm, 0.5 A, 250 V, time-delay
- Fuse, cartridge; 5 x 20 mm, 1 A, 250 V, time-delay

Warranty

- Five year warranty on parts and labor

Recommended accessories

- 174-4401-xx, USB cable, type A to type B cable – three feet
- 174-5194-xx, USB cable, type A to type B cable – six feet
- 012-1732-xx, BNC cable assembly, 0 to 1 GHz, shielded – three feet
- 159-0568-xx, Fuse, cartridge; 5 x 20 mm, 0.5 A, 250 V, time-delay
- 159-0569-xx, Fuse, cartridge; 5 x 20 mm, 1 A, 250 V, time-delay



Tektronix is registered to ISO 9001 and ISO 14001 by SRI Quality System Registrar.



Product Area Assessed: The planning, design/development and manufacture of electronic Test and Measurement instruments.

ASEAN / Australasia (65) 6356 3900
Belgium 00800 2255 4835*
Central East Europe and the Baltics +41 52 675 3777
Finland +41 52 675 3777
Hong Kong 400 820 5835
Japan 81 (3) 6714 3010
Middle East, Asia, and North Africa +41 52 675 3777
People's Republic of China 400 820 5835
Republic of Korea +822 6917 5084, 822 6917 5080
Spain 00800 2255 4835*
Taiwan 886 (2) 2656 6688

Austria 00800 2255 4835*
Brazil +55 (11) 3759 7627
Central Europe & Greece +41 52 675 3777
France 00800 2255 4835*
India 000 800 650 1835
Luxembourg +41 52 675 3777
The Netherlands 00800 2255 4835*
Poland +41 52 675 3777
Russia & CIS +7 (495) 6647564
Sweden 00800 2255 4835*
United Kingdom & Ireland 00800 2255 4835*

Balkans, Israel, South Africa and other ISE Countries +41 52 675 3777
Canada 1 800 833 9200
Denmark +45 80 88 1401
Germany 00800 2255 4835*
Italy 00800 2255 4835*
Mexico, Central/South America & Caribbean 52 (55) 56 04 50 90
Norway 800 16098
Portugal 80 08 12370
South Africa +41 52 675 3777
Switzerland 00800 2255 4835*
USA 1 800 833 9200

* European toll-free number. If not accessible, call: +41 52 675 3777

For Further Information. Tektronix maintains a comprehensive, constantly expanding collection of application notes, technical briefs and other resources to help engineers working on the cutting edge of technology. Please visit www.tektronix.com.

Copyright © Tektronix, Inc. All rights reserved. Tektronix products are covered by U.S. and foreign patents, issued and pending. Information in this publication supersedes that in all previously published material. Specification and price change privileges reserved. TEKTRONIX and TEK are registered trademarks of Tektronix, Inc. All other trade names referenced are the service marks, trademarks, or registered trademarks of their respective companies.



21 Aug 2015 75W-60160-0

www.tektronix.com

Tektronix®