

FIXED FILTERS, Bandpass (cont.)

Part Number	Center Freq (GHz)	1dBc Passband (GHz)	Insertion Loss in Passband (dB)	Package	ECCN
FB-1575SMG	15.75	14.60-16.90	2.00	SMG	EAR99
MFBP-00009PSM	15.85	14.10-17.85	1.86	5mm QFN	EAR99
MFBA-00001PSM	16.00	14.10-17.90	2.40	5mm QFN	EAR99
MFBC-00010PSM	16.50	14.60-18.90	1.70	5mm QFN	EAR99
◆ MFBP-00107PSM*¹	16.75	15.50-18.00	2.40	5mm QFN	EAR99
MFBP-00030PSM	16.94	16.19-17.72	3.16	5mm QFN	EAR99
◆ MFBP-00083CSP3*¹	17.00	16.00-18.00	-	3.5mm CSP3	EAR99
MFBC-00004PSM	17.50	14.90-19.90	1.60	5mm QFN	EAR99
MFBP-00060PSM	17.60	13.8-22.5	0.95	5mm QFN	EAR99
MFBC-00011PSM	18.50	16.15-20.70	1.70	5mm QFN	EAR99
◆ MFBP-00061CSP3*¹	19.00	17.80-20.20	-	3.5mm CSP3	EAR99
MFBP-00034PSM	19.61	18.05-21.3	2.25	5mm QFN	EAR99
MFBC-00012PSM	20.30	17.20-23.40	1.55	5mm QFN	EAR99
MFBP-00036PSM	20.56	17.55-24.09	1.55	5mm QFN	EAR99
MFBC-00005PSM	22.00	18.60-25.10	1.40	5mm QFN	EAR99
MFBA-00002PSM	22.20	18.10-26.00	1.80	5mm QFN	EAR99
MFBP-00035PSM	22.47	20.56-24.55	2.21	5mm QFN	EAR99
MFBC-00013PSM	22.50	19.50-26.20	1.50	5mm QFN	EAR99
MFBP-00037PSM	25.70	22.45-29.43	1.58	5mm QFN	EAR99
MFBC-00014PSM	25.75	22.20-29.90	1.75	5mm QFN	EAR99
MFBC-00006PSM	28.00	23.60-32.20	1.60	5mm QFN	EAR99
◆ MFBP-00062CSP3*¹	28.75	27.50-30.00	-	3.5mm CSP3	EAR99
MFBC-00015PSM	30.00	25.40-34.70	1.39	5mm QFN	EAR99
MFBP-00038PSM	30.71	27.69-34.06	2.05	5mm QFN	EAR99
MFBP-00058PSM	30.90	29.9-32.0	2.74	5mm QFN	EAR99
MFBP-00028PSM	31.52	30.82-32.24	3.25	5mm QFN	EAR99
MFBP-00031PSM	32.58	32.14-33.03	4.31	5mm QFN	EAR99
MFBP-00033PSM	32.63	31.95-33.33	3.35	5mm QFN	EAR99
MFBC-00007PSM	35.00	30.10-39.30	1.50	5mm QFN	EAR99
MFBP-00027PSM	35.13	34.15-36.13	3.10	5mm QFN	EAR99
MFBP-00039PSM	35.63	33.08-38.38	2.46	5mm QFN	EAR99
MFBC-00016PSM	36.00	30.60-41.00	1.21	5mm QFN	EAR99
MFBP-00032PSM	36.04	35.2-36.89	3.45	5mm QFN	EAR99

¹Specs subject to change**LIMITERS**

Part Number	Band (GHz)	Loss (dB)	Flat Leakage (dBm)	Average Power Handling (W)	Peak Power Handling (W)	P1dB (dBm)	Package	ECCN
DLM-10SM¹	DC-10	0.75	Adjustable	0.5	—	+10	3mm QFN	EAR99
HLM-100001PSM¹	DC-10	0.9	+8.5@10GHz	10	—	+11	3mm QFN	EAR99
HLM-20PSM¹	DC-20	0.5	+13@20GHz	5	50	+15	4mm QFN	EAR99
HLM-40PSM¹	DC-40	0.5	+15@20GHz	2.5	9.5	+14	4mm QFN	EAR99
HLM-8010CSP1¹	DC-40	0.5	+11@20GHz	1.9	3.2	+11	1.5mm CSP1	EAR99
◆ HLM-70CSP2*¹	DC - 70	0.5	+13@40GHz	1	—	+15	2.5mm CSP2	EAR99

¹Power ratings are dependent on frequency, temperature, and pulse conditions